

WAD 101 Set, 1-channel hot air station 105 W / 230 V



- for hot air irons or soldering cobbles up to 100 W
- Temperature range adjustable
- LED display
- Temperature range: $\pm 30^{\circ}\text{C}$ ($\pm 54^{\circ}\text{F}$)

item number	WL17069
model	WAD 101
model line	WAD
manufacturer	WELLER
manufacturer item number	T0053266699N
GPSR manufacturer information	WELLER Tools GmbH Carl-Benz-Strasse 2 DE-74354 Besigheim www.weller.eu
length	175 mm
width	135 mm

Products for the electronic industry



height	102 mm
scope of supply	1x PU WAD101 supply unit 1x hot air piston HAP 1 1x safety support KH 27 1x hot air nozzle R04, round Ø 1.2 mm 1x changing tool for nozzles 1x jack plug 3.5 mm 1x mains plug 1x Operating instructions
length in inches	6.98 in
width in inches	5.31 in
height in inches	4.02 in
order unit	1 piece
content unit	1 piece
power	105 W
fuse	T 630 mA
voltage	230 V
air volume max	10 l/min
temperature range °C	50 – 550 °C
temperature range °F	150 – 999 °F
temperature accuracy °F	±17 °F
station type	hot air station
air consumption	10 l/min
temperature stability °C	±2 °C
temperature stability °F	± 5 °F
number of channels	1
ESD safe	no