

## WT 1013, digital 1-channel soldering station, 95 W

---



### This is soldering today

The detailed LC display provides an unprecedented overview of all functions, quickly and easily accessible via the new user-friendly menu button. The lightning-fast exchange of the heating element during operation makes it possible to work with several tips in quick succession. If a tip needs to be replaced, this is done independently of the heating element - which saves enormous costs.

### Front-mounted power switch

The front-mounted power switch ensures easy operation at all times.

### Multifunctional LC display

Unique LC display with detailed overview of all functions. Adjustable backlight. The power bar graph allows you to visually check the current power of the soldering station.

### Convenient menu button

The new menu button ensures maximum user-friendliness and easy navigation in the

menu structure.

#### Space-saving

The WT 1 / WT 1H can be stacked on top of the WTHA 1 to ensure more space at the workstation.

#### 2-in-1 WSR tray

The plunger holder can be rotated 180°. The user can choose between wet and dry cleaning.

- locking function
- Display: LCD / Backlight
- equipotential bonding
- WT compatible
- Soldering tip family LT

<b>item number</b>	<b>WL39985</b>
model	WT 1013 Set
model line	WT 1
manufacturer	WELLER
manufacturer item number	T0053441699N
length	149 mm
width	138 mm
height	101 mm
length in inches	5.87 in
width in inches	5.43 in
height in inches	3.98 in
order unit	1 piece
content unit	1 piece
frequency	50/60 Hz
power	95 W
nominal power	95 W
voltage	230 V
fuse	0.5 A
temperature range °C	50 – 450 °C
temperature range °F	150 – 850 °F
temperature accuracy °F	±17 °F
station type	soldering station

Products for the electronic industry



included stand	WSR 201
included soldering tip	LT B
included control unit	WT 1
included soldering iron	WP 80
number of channels	1
ESD safe	yes