

## Torque adapter 0.6Nm for 1/4 inch bits



preset torque, accuracy tolerance +/-10%. precise and accurate, for 20.000 clicks. In combination with power tool max. speed 100 rpm.

- Diameter: Adapter  $\varnothing$  8 mm
- Torque adapter length 28 mm (without shaft)
- Magnetic bit receptacle 6.35 mm (1/4 inch), 6-point shaft 6.35 mm (1/4 inch), 6-point Shaft 6.35 mm (1/4 inch)

Item no.	WL48480
Model	4-981
Manufacturer	BERNSTEIN
Manufacturer article no.	4-981
GPSR manufacturer data	BERNSTEIN Werkzeugfabrik Industriehof Trecknase 1

Products for the electronic industry



DE-42897 Remscheid  
[www.bernstein-werkzeuge.de](http://www.bernstein-werkzeuge.de)

Scope of delivery	individually packed
Sales unit	1 piece
Content unit	1 piece
Material	Material alloy steel HRC 43-48
VDE	no
ESD compliant	no
Adapter (torque)	0.6 Nm
Tool length	39 mm

## Other versions

Item no.	Adapter (torque)
<b>WL48480</b>	<b>0.6 Nm</b>
WL48481	0.9 Nm
WL48369	1.2 Nm
WL48213	1.4 Nm
WL48214	2.0 Nm
WL48482	3.0 Nm